

### 4 Zone, 6 Source

The AX-400DA features 4 powered zones delivering 50 watts per speaker and 6 digital/analogue sources.

### Endless Connectivity

USB (for configuration), RS232, IR BUS and Ethernet connectivity, 8 buffered IR outputs, 2 lit doorbell compatible triggers, individual amp on's, keypad connections and an amplifier expansion port offering unrivalled connectivity of up to 96 Zones.

### Unrivalled Control

The internal webpage has unique customization allowing IR commands to be attached to buttons for source control from the webpage offering source and zone lockout via customizable user accounts and the ability for built-in automation via Zone and Source event triggers. iOS and Android App compatibility. By using the **FREE** app you can use the Amplifier as a controller with macro capability. Add the KPC-N 2.8" colour touchscreen and enjoy full two way communications from each zone on both interfaces. A **FREE** Control4 driver is also available

### Audio Control

Adjustable input levels, Bass, Treble, balance and 14 presets. Zone linking and 2 doorbell inputs for stored music.

Prepare to be spellbound in every room....



## Technical Specifications

- 50 Watts per channel @8Ω (4Ω capable)
- Output short circuit, thermal and clipping protection
- Analogue input level gain adjustment
- Expandable to 96 zones
- Bass, Treble, Balance Loudness adjustments per zone
- 8 Audio Sources:
  - S1 - 4 either Analogue, or Digital Coax (PCM)
  - S5 - S6 either Digital Coax or Optical (PCM)
  - Storage for up to 10 seconds of 44.1 KHz 16 Bit stereo audio for the doorbell
- 8 Buffered IR outputs
  - 1 - 6 routing
  - 7 - 8 summed
- Send IR from the keypad ports to a controller
- Internal Web Page with user access control
- iOS and Android compatible via **FREE** app
- Zone and Source event triggers
- Backward compatible, adding Ethernet connectivity and control to legacy systems
- Extensive zone linking
- Keypad/IR connection for every zone
- USB, RS232 and Ethernet interface
- 14 amplifier presets and two page presets
- AMP-ON status: 12VDC Outputs
- Setup lockout
- Static and DHCP network connections
- KNX support - *Weinzierl IP BAOS 771 required*
- Control4 driver available - **FREE**
- Power Supply: 90 – 240VAC 50/60 HZ
- Power Consumption: 320 WRMS
- Standby Power: 6W
- Dimensions: 435 x 90 x 390 mm
- Height including feet: 105mm
- Weight: 7.5Kg - *excluding packaging*

*Specifications and features subject to change without notice. Please check [www.axium.co.nz](http://www.axium.co.nz) for latest updates*

