

“NEW” AXIUM AX-AMM2 MEDIA MANAGER



The AMM2 has been re-engineered. We have included an HDMI output connection to connect the AMM2 directly to a home theatre receiver or TV as well as the AMM2 having a Line Out Analogue connection. The 4 digital output connections have been removed.

HDMI Output, Line Out, USB input and 8 network streams total

The AX-AMM2 features 1 x HDMI output and 1 x Lineout with 8 internal network streamers. The AX-AMM2 supports Apple Airplay, Spotify Connect, Pandora accounts, TuneIn radio, Network shares (UPnP, SMB), play from your device and Axiu Favorites. The AX-AMM2 supports a large list of audio files. Included in this list is AAC (MPEG4), FLAC (lossless) and WAV files. The AX-AMM2 supports up to 96 kHz sampling rates.

Simple setup

Complete customization is also available via ADP where you can (among other things) select what streaming services to allow. Plug the AMM2 into the network along with an Axiu AX-Mini4 or AX-1250 amplifier for quick and easy plug and play connectivity when using the Axiu mobile Self-discover app.

Any source from any amplifier and the Media Manager can be accessed in any Zone



Axiu AX-AMM2

“NEW” AXIUM AX-AMM2 MEDIA MANAGER



Technical Specifications

-)} Apple Airplay for each media player stream**
-)} Spotify Connect for each media player stream**
-)} Multiple Pandora accounts supported**
-)} Tuneln Internet streaming**
-)} 10 Audio Streams
 - o 1 HDMI
 - o 1 analogue 3.5mm jack
 - o 8 Network streams over LAN
-)} Local mobile device music playback (iOS and Android) and UPnP push functionality
-)} Network share (NAS or PC) playback (UPnP, DLNA and SMB)
-)} 8 Network Audio Streams
-)} Support for up to 96 KHz 16 Bit stereo audio
-)} Auto integration into AX-Mini 4 and AX-1250 media players
-)} KPC-N applet
-)} Alarm capabilities via amplifier
-)} Powered by 5VDC 3A power supply
-)} Static or DHCP network connections
-)} Dimensions: 94 L x 60 W x 26 D mm

Audio formats supported as of December 2016	
MP3	Standard and variable bit and sample rates
WAV	8 and 16bit PCM up to 48kHz. No metadata. (96kHz)
M4A/MP4	Up to 48kHz and 576kBits/s. (96kHz)
AAC	48, 96K
OGG/OGA	2Ch, 500kBits
FLA C	Up to 48 kHz and 24 bit 96kHz
HD FLAC 24 / 96	24,96K
HD WAV	24,96K
ALAC	24, 96K

* AX-Mini 4 has access to the network streams

* AX-1240 has access to the 8 network streams

**An internet connection is required Internet streaming services. ISP charges may apply. Future services may be added. Pandora is not available in Australasia.

Specifications and features subject to change without notice. Please check www.axiumcontrols.com for latest updates.

NOTE: If you are using a version 2 AMM, select version 2 as per below in ADP if using Axiom ADP for programming

